

Mixing amplifier

MA-30/60/120D

100V/4-16Ω



Features:

- Tabletop mixer amplifier with media player
- Built-in medial player with USB/SD, FM/DAB+ & Bluetooth
- Rated power output at 30W, 60W to 120W
- Speaker output of 100V or 70V & 4-16Ω
- 3 x mic/line inputs, 2 x RCA line inputs, 1 x TEL input and 1 x RCA line output
- XLR input with switchable +48V phantom power
- With short-circuit, clip, overload and high temp protection
- 230V AC or 24V DC power supply

Technical specifications

Model	MA-30D	MA-60D	MA-120D
Description	Tabletop Mixer Amplifier with USB/SD & FM/DAB+ & Bluetooth		
Rated Power Output	30W	60W	120W
Speaker Outputs	100V or 70V & 4-16Ω		
Connector	Mic1 input by balanced XLR with phantom power Input2-3 inputs Mic/Line switchable unbalanced 6.3mm jack Line1-2 inputs by RCA, Tel input with MOH, Line output by RCA		
Input	Mic1-3: 5-8mV, 600Ω; Line & TEL: 150-470mV, 10KΩ, unbalanced RCA		
Line Out	0.775(0dBV)		
Frequency Response	60Hz-15kHz(±3dB)		
S/N Ratio	Line ≥ 85dB, Mic ≥ 72dB		
THD	Less than 0.5%		
Protection	short-circuit, clip, overload and high temp protection		
Power Consumption	60W	100W	200W
Power Supply	230V AC & 24V DC; 50-60Hz		
Dimension	320×210×90mm		
Weight	3.7kg	4.3kg	4.9kg